

ROLBAT M1 1000

**ROLL
FORCE**

Motor para cortina de 1000 Kg con una elevación máxima de 9 metros y respaldo de batería.

Voltaje de entrada	120 Vac
Corriente	15A
Potencia	430W
Elevación de carga	1000 Kg
Diámetro de tubo	6"
Par de salida	809N.m
Velocidad de salida	5.3r/min
Distancia máxima de elevación	9m
Rango de temperatura ambiente	-20°C - +50°C
Distancia del control	30m
Voltaje del motor	24 Vcc

57 cm

27 cm



BATTERY BOX

POINT FOR ATTENTION

1. Finished the installation of Controller and battery box, plug in the power and open the controller. Firstly, battery joint inserts the main-board and then put into the fuse box, the unit can charge the battery.
2. When the supply power is cut off, the controller continues to use for two days. If the alarm occurs, please charge the battery right away.
3. When the controller has been charged for ten hours, cut off the supply power and appear the alarm, please replace the battery.
4. When the battery box need to back out or storage, the battery may be charged for ten hours before.